MAXWATT ®
POWER WHEN YOU NEED IT

The Maxwatt MX11000i 2 wire auto start generator has been designed to provide back up power for off grid solar systems. It has a pre installed 2 wire automatic control system. This generator can automatically provide backup to recharge the storage battery and feed-in power to supply the load.

The Maxwatt range of generators have been manufactured using only high-quality components and designed to last in the toughest conditions.

2 YEAR WARRANTY

MX11000I
Barcode: 9356905000302

❯ **Home / Solar Off The Grid**
GENERATORS

9000W Petrol Electric Start Generator with 2 Wire Auto Start

Remote Control Start

PUSH BUTTON / RECOIL START

2 - WIRE AUTO START
inverter

SOLAR OFF GRID READY

34L FUEL TANK

- Electric starting system (Battery included)
- 4 Stage digital meter display
- Automatic voltage regulator
- Low oil alert sensor
- Solar off grid ready
- Light weight
- Thd>3%
- 3 X Outlets
  1 X 15 Amp IP44
  1 X 15 Amp IP 66
  1 X 32 Amp IP66
- Superior quality SENCI alternator
- 34L Large capacity fuel tank
- Large muffler design to reduce noise
- Heavy duty 32mm frame with wheels and handle

Technical Information

Voltage (V)	240V	Noise Level (dB's) at 7m @ 75% Load	76
Amperage (A)	35.4A	Weight (Net)	78kg
Displacement (cc)	459cc	Ignition	Electric /Remote Control
Fuel Tank Capacity (L)	34L	Rated Frequency	50Hz
Rated Power (Watts)	8500W	Cont. Running Time @50% Load	16 hrs
Max. Power (Watts)	9000W	Cont. Running Time @100% Load	11 hrs

Generator Dimensions
Length 708mm | Width 550mm | Height 656mm | Weight 78kg

Box Dimensions
Length 723mm | Width 570mm | Height 686mm | Weight 85kg

Repair and Technical Information www.maxwatt.com.au Or customercare@maxwatt.com.au